

# LAJ30

## La Jolla

DECORATIVE



### FEATURES



- The cast 6-sided cage shall accommodate UV stabilized acrylic or polycarbonate lenses (side panels) which shall be sealed for weather tight operation. All cast aluminum parts shall be low copper alloy A356. All extruded aluminum parts shall be alloy 6061-T6, 6063-T5 or equal. The upper chamber/lid shall be topped by a decorative cast aluminum finial/cap and mechanically fastened to the optical chamber. The electrical chamber/fitter shall be aluminum, decorative fitter shall mount to 3"OD x 3" H tenon and secured by three stainless steel set screws.
- Each luminaire is supplied with an optical one piece LED bezel assembly, with LEDs, optics, gaskets and stainless steel face-plate. A thermal circuit, called LIFESHIELD™, shall protect the luminaire from excessive temperature by interfacing with the 0-10V dimmable drivers to reduce drive current as necessary.

### ORDERING INFORMATION

LAJ30															
<b>MODEL</b>		<b>ENGINE WATTS</b>		<b>LED COLOR</b>		<b>OPTICS</b>		<b>CONTROL OPTIONS</b>		<b>COLOR</b>		<b>LENS OPTIONS</b>		<b>VOLTAGE</b>	
LAJ30 La Jolla 30"		24NB-55 55 Watts 36NB-80 80 Watts 48NB-110 110 Watts 60NB-136 136 Watts		3K 3000K 4K 4000K 5K 5000K		DIR2 Direct, Type II DIR3 Direct, Type III DIR4 Direct, Type IV DIR5 Direct, Type V		GENI-XX Energeni <sup>2</sup>		BBT Basic Black Textured BMT Black Matte Textured WHT White Textured MBT Metallic Bronze Textured BZT Bronze Textured DBT Dark Bronze Textured GYS Gray Smooth DPS Dark Platinum Smooth GNT Green Textured MST Metallic Silver Textured MTT Metallic Titanium Textured OWI Old World Iron RAL _____		AC Acrylic, Clear AF Acrylic, Frosted AS Acrylic, Seeded AW Acrylic, White PC Polycarbonate, Clear PF Polycarbonate, Frosted		UNV 120-277V 347 347V 480 480V	
						<b>ELECTRICAL OPTIONS</b>		<b>MOUNTING OPTIONS</b>							
						PEC-120 photocell, button 120V PEC-208 photocell, button 208V PEC-240 photocell, button 240V PEC-277 photocell, button 277V		PT Post Top PM Pendant Mount <sup>1</sup>							

<sup>1</sup> Consult factory

<sup>2</sup> When ordering Energeni, specify the routine setting code (example GENI-04). See Energeni brochure and instructions for setting table and options.



Visit [www.beaconproducts.com](http://www.beaconproducts.com) for up-to-date availability information